

sanwa®

TOKYO JAPAN

DIGITAL MULTIMETER

PC710

APPLICATIONS AND FEATURES

This instrument is a portable multimeter designed for the measurement of low-voltage circuit. This is used at small communications equipments, home electric appliances, voltage of lump line, various types of batteries, and circuit analyses with additional functions.

- AC True RMS / 9999 count & 6000 count
- 0.06% best accuracy
- Dual display capability with Backlight to simultaneously display voltage/current/frequency and AC/DC components of voltage/current
- High speed bar graph
- Electric Field(EF) detection
- Conductance measurement / Capacitance measurement
- Temperature measurement (with K type thermocouple sensor : -50°C~1000°C)
- Frequency measurement (AC sine wave only)
- Logic frequency measurement / Duty cycle measurement
- MAX, MIN, AVE value hold / Data hold / Range hold
- Relative value
- Auto power save (30min after the last operation)(cancelable)
- Backlight
- Protective holster with wall hanger and lead holder / Tilt stand
- PC Link system with optical Link USB cable (KB-USB7) and software(PC Link7)

*KB-USB7 and PC Link7 are optional accessories

SPECIFICATIONS

| | Measuring range | Best accuracy | Resolution | Input impedance |
|-----------------|---------------------------------------|---------------|------------|-----------------|
| DCV | 60m/600m/9.999/99.99/999.9V | ±(0.06%+2) | 0.01mV | 10MΩ |
| ACV | 60m/600m/9.999/99.99/999.9V | ±(0.5%+3) | 0.01mV | |
| DCA | 600μ/6000μ/60m/600m/6/10A | ±(0.2%+4) | 0.1μA | |
| ACA | 600μ/6000μ/60m/600m/6/10A | ±(0.6%+3) | 0.1μA | |
| Resistance | 600/6k/60k/600k/6M/60MΩ/99.99nS *1 | ±(0.1%+3) | 0.1Ω | |
| Capacitance | 60n/600n/6μ/60μ/6m/25mF | ±(0.8%+3)*2 | 0.01nF | |
| Temperature | -50°C~1000°C(thermocouple K type) | ±(0.3%+2) | 1°C | |
| Frequency | 15Hz~50kHz | ±(0.04%+4) | 0.01Hz | |
| Logic frequency | 5Hz~1MHz | ±(0.03%+4) | 0.001Hz | |
| Duty cycle | 0%~100% | ±(3d/kHz+2) | 0.01% | |
| Continuity | Buzzer sounds at between 20Ω and 300Ω | | | |
| Diode test | Open voltage: approx. 1.2V | | | |

*1 nS(Conductance): High-value resistance of Giga-Ohms for leakage measurements. Conductance is the inverse of Resistance, that is $S=1/\Omega$ or $nS=1/G\Omega$

*2 Accuracy of film capacitor or equivalent with low leakage.

A battery for monitoring has been installed prior to shipment from the factory. It may be discharged before the expiration of the described battery life. This battery is used to check the functions and performance of the product. Specifications and external appearance of the product described above may be revised for modification without prior notice.



CE

sanwa

SANWA ELECTRIC INSTRUMENT CO., LTD.

Dempa Bldg, 4-4 Sotokanda 2-Chome, Chiyoda-Ku, Tokyo 101-0021 Japan
Tel:+81-3-3251-0941 Fax:+81-3-3256-9740

www.sanwa-meter.co.jp

Distributed by

sanwa

A M E R I C A

AUTHORIZED DISTRIBUTOR

www.sanwa-america.com